



Tri-Mitter

Advantages

- ▶ Top-design wireless switch
- ▶ Switching or dimming of up to 3 independent 12 V or 24 V circuits
- ▶ For impressive lighting effects in furniture

Features

- ▶ The 3 channels of the receiver can be switched individually or together by the TRI-Mitter
- ▶ Memory function for power failure

Examples of use

- ▶ Furniture lighting

Ordering information

- ▶ Kit consists of Tri-Mitter receiver, Tri-Mitter hand-held wireless transmitter and drill-hole mounting ring
- ▶ Only for use with dimmable LED lamps
- ▶ AppMitter for control from smartphone

Technical details in brief



Can be used with:	LED lights
Surface finish:	Aluminium look
Plug connection IN:	LED mini plug connection M1 / MP2
Plug connector OUT:	M1 / MP2
Switching voltage:	12 / 24 V DC
Max. switching power:	3 x 36 W / 3 x 72 W
Test marks and symbols:	CE ◊ ▼▼
Supply lead:	160 mm
Switching lead:	160 mm
Standby:	0.3 W

Tri-Mitter (wireless switch)

Article	Order no.
Tri-Mitter wireless switching kit 12 V DC	30 588 01
Tri-Mitter wireless switching kit 24 V DC	30 589 01
Tri-Mitter wireless hand-held transmitter	30 590 01

Accessories (for more accessories, see chapters "Switch systems" and "Ballasts & leads")

Article	Order no.
Repeater 12 V (max. 36 W)*	30 263 07
Repeater 24 V (max. 72 W)*	30 263 08
AppMitter Bluetooth power socket dongle	30 578 01

* one repeater allows for the control of more than 36 W at 12 V and 72W at 24 V, respectively

Dimensional drawing / installation

